



# kramer

## VGAA-IN8-F64

8-Channel VGA with Analog Audio Input Card

| Kramer Core



VGAA-IN8-F64 is an eight-channel VGA with analog audio input card for the VS-6464 Series Modular Multi-Format Digital Matrix Switchers. The VGAA-IN8-F64 inputs eight VGA with analog audio signals into the chassis. Audio is accessed by connecting the supplied Kramer VGA with audio cables to each VGA port

### FEATURES

- Max. Bandwidth - 450MHz
- HDTV Compatible
- Analog Audio Over Breakaway Connector



# kramer

## TECHNICAL SPECIFICATIONS

---

|                                      |   |
|--------------------------------------|---|
| PORTS:                               | 8 VGA on 15-pin HD connectors, 8 unbalanced analog audio on 3.5mm mini jack connectors (accessible via C GF/GMAF-30 cables) |
| BANDWIDTH:                           | 450MHz  |
| MAXIMUM RANGE:                       | 10m (32ft)  |
| POWER CONSUMPTION:                   | 35W   |
| OPERATING TEMPERATURE:               | 0° to +40°C (32° to 104°F)  |
| STORAGE TEMPERATURE:                 | -40° to +70°C (-40° to 158°F)   |
| HUMIDITY:                            | 10% to 90%, RHL non-condensing  |
| SAFETY REGULATORY COMPLIANCE:        | CE  |
| ENVIRONMENTAL REGULATORY COMPLIANCE: | Complies with appropriate requirements of RoHs and WEEE   |
| INCLUDED ACCESSORIES:                | 8 C-GF/GMAF-30 cables   |
| Product Dimensions                   | 39.50cm x 18.00cm x 2.00cm (15.55" x 7.09" x 0.79" ) W, D, H  |
| Product Weight                       | 0.4kg (1.0lbs) approx   |
| Shipping Dimensions                  | 54.80cm x 27.50cm x 10.60cm (21.57" x 10.83" x 4.17" ) W, D, H  |
| Shipping Weight                      | 0.8kg (1.7lbs) approx   |